



(slika je simbolična)

TP-LINK Archer TX3000E AX3000 Wi-Fi 6 Bluetooth 5.0 PCI express 2402Mbps(5GHz)+574Mbps(2,4GHz) adapter

Kategorija: [Mrežne kartice](#)

Dobavljivost: **predvidena dobava 21.08.2026**

Šifra: **54951**

Cena: 44,69€ 48,75€

Kratek opis

Podrobno o izdelku:

Proizvajalčeva koda	ARCHER TX3000E
EAN koda:	6935364088897
Proizvajalec:	TP-LINK
Standard:	Wi-Fi 6, Bluetooth 5.0
Garancija	36 mesecev
razprodaja	No
Povezava kartice/adapterja:	brežžična
Dodatne lastnosti kartic/adapterja:	Bluetooth, Dual Band, priklonpa postaja, zunanja antena
Priklop kartice/adapterja:	PCI express
Tip mrežne kartice/adapterja:	IEEE 802.11ax WiFi6
Vsebina paketa:	Archer TX3000E magnetizirana osnova antene z 1 m RF kablom 2x 5 dBi High Gain anteni konzola z nizkim profilom Bluetooth Header kabel

dimenzija: 95,2 x 120,8 x 21,5 mm
tip antene: 2x high gain Dual band antena, magnetna podlaga antene
nabor čipov: Intel Wi-Fi 6
BREZZIČNI STANDARD
IEEE 802.11ax/ac/n/a 5 GHz
IEEE 802.11ax/n/g/b 2.4 GHz
Bluetooth 5.0/4.2/4.0
WLAN Signal Rate:
5 GHz
11ax: Up to 2402 Mbps (dynamic)
11ac: Up to 1733 Mbps (dynamic)
11n: Up to 300 Mbps (dynamic)
11a: Up to 54 Mbps (dynamic)

2.4 GHz
11ax: Up to 574 Mbps (dynamic)
11n: Up to 300 Mbps (dynamic)
11g: Up to 54 Mbps (dynamic)
11b: Up to 11 Mbps (dynamic)

WLAN Reception Sensitivity:
5 GHz :

11ax HT160: -56.25dBm
11ax HT80: -59dBm
11ax HT40: -62.25dBm
11ax HT20: -65dBm
11ac HT160: -62dBm
11ac HT80: -65.5dBm
11ac HT40: -69.75dBm
11ac HT20: -73.75dBm
11n HT40: -74.5dBm
11n HT20: -77.5dBm
11a 54Mbps: -77.75dBm
11a 6Mbps: -94.5dBm

2.4GHz :

11ax HT40: -60.75dBm
11ax HT20: -63.75dBm
11n HT40: -73dBm
11n HT20: -76.25dBm
11g 54Mbps: -76.5dBm
11b 11Mbps: -89dBm

WLAN Transmit Power

5 GHz : 27dBm(FCC) / 23dBm(CE) (EIRP)

2.4 GHz : 26dBm(FCC) / 20dBm(CE) (EIRP)

brezžična varnost: Support 64/128 bit WEP, WPA/WAP2/WPA3, WPA-PSK/WPA2-PSK, 802.1x

Bluetooth profili: Archer TX3000E podpira domače BT profile, implementirane v sistemu Windows

10. Za najnovejše informacije o Windows 10 BT profilih glejte

<https://support.microsoft.com/en-us/help/10568/windows-10-supported-bluetooth-profiles>

Dodatno: